



KINETIC WIRELESS SWITCHES RECEIVERS

DESCRIPTION:

NEW TECHNOLOGY Greenhouse Kinetic RF Switch Receivers

Connect Wirelessly with Kinetic Switches.

Various controllers/receivers available -
 Dual Receiver: **GH-SWR**
 Dimmer Receiver: **GH-SWRD**
 Tuya Smart Receiver : **GH-SWR WIFI**
 Tuya Smart DimmerWiFi Receiver: **GH-SWRD WIFI**

Google and Alexa compatible with Smart WiFi receiver

KEY INFORMATION

DUAL RECEIVER GH-SWR	Max 5A LED 600W (1 Way), Max 5Ax 2 LED 600Wx2 (2 Way), Max 10A LED 1000w, Min load 5w Max 10 switch keys per channel
DIMMER RECEIVER GH-SWRD	Rated Power LED 100W, Min load 5W Max 10 switch keys can be paired
TUYA SMART RECEIVER GH-SWR WIFI	Max 5A LED 600W, Max current 5A Max 10 switch keys can be paired
TUYA SMART SMART DIMMER WIFI RECEIVER	Rated Power 100W, Min load 5w Max 10 switch keys per channel
VOLTAGE	200-240V 50/60 Hz
RADIO FREQUENCY	RF 433MHz (+ WiFi 2.4GHz Smart Option)
MATERIAL CONSTRUCTION	Polycarbonate
IP RATING	IP20 Indoor Use Only
INSTALLATION	Screw/ 3M Tape
TRIM COLOUR	White
DIMENSIONS	90mmx44x35mm
OPERATING RANGE	Up to 80m Outdoors, 25m Indoors
WARRANTY	3 Years
CERTIFICATION	SAA, RCM