EYE 360 Recessed Microwave Security Sensor

A small ceiling-recessed microwave sensor that turns indoor lights on when it senses movement, all around it.



KEY FEATURES

- 360° detection, up to 16 m across
- Senses through glass, plastic and thin non-metal materials
- Set time, lux level and detection area
- Recessed in the ceiling – 65 mm hole
- Switches up to 150 W of LED lights
- Indoor use only

IN THE BOX

- 1 × EYE 360 recessed microwave sensor (white) with spring clips

SPECIFICATIONS

Type	Microwave (HF) motion sensor, 3-wire
Frequency	5.8 GHz
Supply voltage	240 V AC
Detection range	360°, up to 16 m diameter
Mounting height	1.5–3.5 m
Time on	10 seconds to 12 minutes
Lux level	3–2000 lux (adjustable)
Max. load	1200 W incandescent, 300 W fluorescent, 150 W LED
Manual override	No
Cut-out	65 mm
Size	Ø76 × 77 mm
IP rating	IP20 – indoor use only
Material	White UV-resistant polycarbonate
Warranty	2 years replacement

Installation: licensed electrician required – see the installation guide. Keep your invoice for warranty.

EYE 360 Recessed Microwave Security Sensor

ABOUT THIS PRODUCT

The EYE 360 is a compact microwave motion sensor that recesses neatly into the ceiling and switches indoor lights on when someone moves nearby. It watches a full 360° circle up to 16 m across and can even sense through glass, plastic and thin non-metal panels. Time on, light level and detection area are all adjustable, so lights only come on when needed. It is ideal for hallways, garages, laundries and storerooms, and switches up to 150 W of LED lighting.

MORE DETAILS

Activation	Motion plus light level (lux) control
Mounting	Recessed into the ceiling, needs a 65 mm hole
Detection area	Adjustable

SAFETY & COMPLIANCE

Compliance details being updated

Greenhse supplies this product for sale in Australia. Its updated compliance documents are being finalised. Please contact Greenhse for the latest certificate details before installation.