Flexiscan IP66 PIR Security Sensor

A weatherproof motion sensor that turns outdoor lights on when someone moves nearby, with an adjustable arm.



KEY FEATURES

- 110° detection, up to 18 m away
- Adjustable arm – easy to aim
- Set time, sensitivity and lux level
- Manual override – back to Auto after 8 hours
- Handles big loads: up to 300 W of LED lights
- IP66 – wall or ceiling, outdoors

IN THE BOX

- 1 × Flexiscan PIR sensor (beige or black) with adjustable arm and mounting base

SPECIFICATIONS

Type	PIR (passive infra-red) motion sensor, 3-wire
Detection range	110° × 18 m
Time on	10 seconds to 20 minutes
Adjustments	Time, sensitivity and lux level
Manual override	Yes – resets to Auto after 8 hours
Max. load	2400 W incandescent, 1200 W fluorescent, 300 W LED
IP rating	IP66 – outdoor use
Mounting	Wall or ceiling, adjustable arm
Lens	Multi-segmented lens
Material	UV-resistant polycarbonate
Finish	Beige or black
Operating temperature	–5 °C to +45 °C
Warranty	5 years

OPTIONS

Code	Finish
Flexiscan-beige	Beige
Flexiscan-black	Black

Installation: licensed electrician required – see the installation guide. Keep your invoice for warranty.

Flexiscan IP66 PIR Security Sensor

ABOUT THIS PRODUCT

The Flexiscan is a weatherproof IP66 PIR motion sensor that turns outdoor lights on when someone approaches. It covers a 110° area up to 18 m away, and the adjustable arm lets you aim it exactly where you need it on a wall or ceiling. Set the time, sensitivity and light level to suit, or use manual override to keep the lights on, which returns to auto after 8 hours. It handles up to 300 W of LED lighting and comes in beige or black.

MORE DETAILS

Detection method	Passive infra-red, multi-segment lens
Wiring	3-wire design
Manual override	Returns to auto after 8 hours

SAFETY & COMPLIANCE

Compliance details being updated

Greenhse supplies this product for sale in Australia. Its updated compliance documents are being finalised. Please contact Greenhse for the latest certificate details before installation.