Kinetic Plug-in Socket Receiver and Switches

A plug-in socket that turns any plugged-in lamp or appliance on and off from a battery-free kinetic wall switch, or from your phone with the WiFi model.





KEY FEATURES

- No wiring – plug it into a power point
- Works with 1, 2, 3 or 4 gang kinetic switches (no batteries)
- WiFi model works with the Tuya Smart / Smart Life app
- WiFi model works with Google and Alexa voice control
- Switches stick to glass, tile, marble or walls, or use as a remote
- Range up to 20 m indoors

IN THE BOX

- 1 × plug-in socket receiver (standard or WiFi)
- Switches sold separately

SPECIFICATIONS

Input voltage	110–240 V AC, 50/60 Hz
Maximum load	600 W LED
Frequency	RF 433 MHz; WiFi model adds 2.4 GHz WiFi + Bluetooth
Range	Up to 20 m indoors
Socket size	49 × 49 × 53 mm
Material	White fire-rated polycarbonate
IP rating	Socket IP20, switch IP42 (indoor)
Indicator	Red = switch pairing; blue = WiFi pairing (WiFi model)
Switches	1, 2, 3 or 4 gang, self-powered
Operating temperature	−20 °C to 50 °C
Approvals	See page 2
Warranty	2 years

OPTIONS

Code	Item	Control
GH-KSR	Kinetic socket receiver	Kinetic switch
GH-KSR-WIFI	WiFi socket receiver	Switch, app or voice
1 gang	1-button kinetic switch	Self-powered
2 gang	2-button kinetic switch	Self-powered
3 gang	3-button kinetic switch	Self-powered
4 gang	4-button kinetic switch	Self-powered

Installation: licensed electrician recommended – see the installation guide. Keep your invoice for warranty.

Certification: RCM

Kinetic Plug-in Socket Receiver and Switches

ABOUT THIS PRODUCT

The Kinetic plug-in socket receiver lets you switch a lamp or plug-in light from a wireless wall switch with no wiring at all. Plug the receiver into a power point, plug your light into it, then stick the battery-free kinetic switch wherever you want it. Pressing the switch makes its own power, so there are no batteries to replace. The WiFi version also works with the Smart Life app, Alexa and Google Home. Each socket handles up to 600 W of LED lighting.

MORE DETAILS

Standby power	Under 0.1 W (standard), under 0.3 W (WiFi)
Case material rating	V0 flame rating (PC and ABS)
Socket weight	63 g
Switch size	86 × 86 × 15.8 mm
Switch power	Self-powered by the press, no battery

SAFETY & COMPLIANCE

Compliance details being updated

Greenhse supplies this product for sale in Australia. Its updated compliance documents are being finalised. Please contact Greenhse for the latest certificate details before installation.