INSTALLATION GUIDE

Product code: remote-control-grp

LED Wireless Remote Controls – 2.4 GHz

Licensed electrician recommended. The remote runs on batteries. The controller and transformer it works with should be installed by a licensed electrician (AS/NZS 3000).

IN THE BOX


- 1 × remote control (model you ordered)

YOU WILL NEED

- 2 × AAA batteries
- Access to the light's power switch

BEFORE YOU START

- Pick the remote to match your lights: dimming remote for single colour, CCT remote for dual white, RGB+CCT remote for colour (RGB / RGBW / RGB+CCT).
- Make sure a compatible 2.4 GHz controller is already installed and working.



To link: power the lights off, back on, then press ON 3 times within 3 seconds

One zone button per group of lights

STEP BY STEP

1. Fit 2 × AAA batteries into the remote.
2. Turn the light's power off and wait 10 seconds.
3. Turn the power back on.
4. Within 3 seconds, press the zone ON button (or ON) 3 times.
5. The light blinks 3 times slowly – the remote is linked.
6. Repeat for each zone, using a different zone button for each group of lights.
7. Glass panel or round remote: stick the holder or magnetic base where you want it.

SETTINGS & USE

- Unlink: power off 10 seconds, power on, then press the same zone ON button 5 times within 3 seconds. The light blinks 10 times quickly.
- A zone is a group of lights that work together. One zone button can control many lights linked to it.
- If linking fails, switch off again and repeat the steps.

DO NOT

- Don't use near large metal surfaces or strong electrical noise – it shortens the range.
- Don't mix old and new batteries.
- Don't press hard on the glass panel – it can break.

CARE & TROUBLESHOOTING

- Wipe with a soft dry cloth.
- Range getting short or no response? Replace the batteries.

Installation: Greenhse recommends that every product is installed by a licensed electrician to AS/NZS 3000 and local rules. Any work on 240 V wiring must be done by a licensed electrician. Incorrect installation can be unsafe and may void the warranty. **Warranty:** 2 years. Keep your invoice and the electrician's certificate of compliance. Questions? Call (08) 9297 2969 or visit greenhse.com.