Smart WiFi Crystal Glass Touch Switch – 1 to 4 Gang

A touch light switch with a glass front that you can also control from your phone, by voice or on a timer.



KEY FEATURES

- Touch glass light switch in 1, 2, 3 or 4 gang
- Control lights from your phone with the Smart Life app
- Voice control with Amazon Alexa or Google Home
- Set timers and schedules from anywhere with internet
- Needs a neutral wire at the switch for stable WiFi
- Scratch-resistant crystal glass, white (black optional)

IN THE BOX

- 1 × smart touch switch (1, 2, 3 or 4 gang) with glass cover plate

SPECIFICATIONS

Type	Smart WiFi touch light switch
Gangs	1, 2, 3 or 4
Input voltage	240 V AC, 50-60 Hz (rated 100–240 V)
Maximum load	1 gang 1000 W; 2–4 gang 2000 W in total, max 1000 W per gang
Wiring	Needs Active and Neutral at the switch
WiFi	2.4 GHz, IEEE 802.11 b/g/n
App	Smart Life / Tuya Smart app
Voice control	Amazon Alexa, Google Home
Indicator light	Light blue = off, dark blue = on
Size	118 × 72 × 34 mm
Wall box size	115 × 60 × 50 mm
Material	Crystal glass front, flame-retardant PC body
Cover colour	White (standard) or black (optional)
Warranty	2 years
Approvals	RCM approved, certified to AS/NZS 60669

OPTIONS

Option	Touch buttons	Maximum load
1 gang	1	1000 W
2 gang	2	2000 W total (1000 W per gang)
3 gang	3	2000 W total (1000 W per gang)
4 gang	4	2000 W total (1000 W per gang)

Installation: licensed electrician required – see the installation guide. Keep your invoice for warranty.

Smart WiFi Crystal Glass Touch Switch – 1 to 4 Gang

ABOUT THIS PRODUCT

A touch light switch with a sleek crystal glass front that also works from your phone, by voice or on a timer. Available in 1, 2, 3 or 4 gang, it replaces a standard wall switch and connects to 2.4 GHz WiFi through the Smart Life app. Turn lights on and off from anywhere, set schedules, or use Amazon Alexa and Google Home. It needs an active and neutral at the switch, which keeps the WiFi link stable. White glass is standard, with black available.

MORE DETAILS

Pairing	Hold the touch button about 3 seconds until the WiFi light flashes fast, then add it in the app
Reset	Hold the touch button until it beeps four times to clear settings
Network	2.4 GHz WiFi only, not 5 GHz
Packed size	145 × 85 × 50 mm

SAFETY & COMPLIANCE

Electrical safety certified for Australia
Certificate SAA-212469-EA, valid to 22 Dec 2026

RCM

Electrical safety certificate	SAA-212469-EA (valid to 22 Dec 2026)
Certificate covers	The smart switch
Compliance mark	RCM (Regulatory Compliance Mark) for electrical safety and EMC
Equipment risk level	Level 3
Greenhse EESS registration	E2026002453 (registered to 22 Dec 2026)
Tested to	AS 60669.2.1:2020; AS/NZS 60669.1:2020
Also	Certificate condition: incandescent load no more than 1000 W per gang and 2000 W in total

Greenhse Technologies is the registered Australian responsible supplier for this product on the national Electrical Equipment Safety System (EESS). Certificate numbers can be checked on the public EESS database at eess.gov.au.